LTECH


E5S Touch Panel (RGBWY)



Manual www.ltech-led.com

System Diagram

LTECH



Wifi-108 can be controlled by remote or local LAN, and supports ECHO amazon voice speakers. The E series panel does not support advanced mode when work with WiFi-108.

Product Features

LTECH


- 2 in 1 function: RF wireless control and PWM power output.
- Power output, lamps can be connected directly, easy and convenient.
- RGB, RGBW, RGB+CT LED lights can be controlled.
- Touch keys with chord and LED indicator.
- Panel adopts capacitive touch control technology, makes LED color selection more user-friendly.
- Touch panel can be controlled by remote directly or smart phone if add a gateway.

00 \\}

22

Technical Specs

| Model: | E5S | | Working Temp.: | -20°C~55°C |
|---------------------|-------------------|---------------|----------------|-------------------|
| Input Voltage: | 12-24Vdc | | Dimensions: | L86×W86×H36(mm) |
| Wireless Frequency: | RF 2.4GHz | | Package Size: | L113×W112×H50(mm) |
| Current Load: | RGB: 3A×3CH CT: M | Max. 3A | Weight(G.W.): | 225g |
| Output Power: | RGB: (0~36W72W)× | 3CH CT: 0~36W | /72W | |




Typical base as below:





Unit: mm






Terminals



Uninstall

Key Functions



★ When blue indicator light of ⁽⁾ key is on, long press ⁽⁾ to turn on/off buzzer. When white indicator light of ⁽⁾ key is on, long press ⁽⁾ to match code.




Application Composition



LTECH

System Diagram


LTECH



Lamps

Wiring Diagram

Connect with 12V strip, RGB Max. 108W, CT Max. 36W. Connect with 24V strip, RGB Max. 216W, CT Max. 72W.





Match Code between Touch Panel & Remote



Match Code between Touch Panel & Gateway



Clear Code



Press the bottom two key on touch panel simultaneously for 5 seconds, the indicator light flicker several times, clear code successfully.

* Please match/clear code when panel is on (white indicator light of 🖒 key is on).

* No further notice if any changes in the manual. Product function depends on the goods. Please feel free to contact your supplier if any question.

LTECH